

DOCUMENT DETAILS <span>V1</span>	
Product:	XS Flow Plus
Type:	QSG
Date Updated:	18-12-2025
Paper Type	250 GSM Thick Card

# XS Flow Plus QSG

## Font

## Back

### Compatible OS

### Specifications

Interface	: Wired + 2.4GHz Wireless + Bluetooth x 3
Buttons	: 8 Buttons
Mouse DPI	: 400 / 800 / 1200 / 1600 / 2400 / 3200 / 6400
Polling Rate	: BT: 250Hz - 2.4G: 1000Hz - Wired: 1000Hz
Sensor	: Instant S203
Chipset	: BK3633
Scroll Wheels	: Metallic main scroll + Hall effect horizontal scroll
Material	: ABS plastic + metal scroll components
Battery	: 800mAh
Switch Type	: Hsuno silent switches, 10 million clicks
Feet	: PTFE Teflon feet
Product Weight	: 112g
Product Dimensions	: 124 x 85 x 50mm

---

### Customer Care

Amkette House, C-64/4, Okhla Phase - II, New Delhi - 110020

1800-11-9090 (Toll Free) (9:30 AM - 6:00 PM)  
+91 9312691448 (9:30 AM - 6:00 PM)

techsupport@amkette.in  
www.amkette.com/register

For Hassle Free Service Register Your Product

### Warranty

Amkette XS Series Flow Plus Dual Scroll Rechargeable Mouse is backed by 2 year performance warranty against any manufacturing defects in material or workmanship from the date of original purchase. This warranty entitles the purchaser to get the product repaired or replaced at its discretion under the following conditions:

The warranty applies to the original purchaser. Proof of original purchase is required.

The warranty does not cover the damage caused by misuse, abuse or improper storage.

In no event shall Amkette be responsible for any direct, incidental, consequential or other damages of any kind.

Please contact our Technical Support Line and/or send the defective product, postage pre-paid, together with the proof of purchase to our Customer Care Service Center to avail warranty service. Return charges will be paid by us.

## XS SERIES

by AMKETTE

# FLOW PLUS

Dual Scroll Rechargeable Bluetooth Mouse

QUICK START GUIDE

Web Control Centre: <https://www.amkette.com/sw/xsflowplus>

### Know Your Mouse

- 1 Vertical Scroll Wheel
- 2 Easy Device Switching
- 3 DPI Button
- 4 Horizontal Scroll Wheel
- 5 Show Desktop
- 6 Mode Indicator
- 7A Forward Button
- 7B Backward Button
- 8 Type C Input
- 9 ON/OFF Switch
- 10 USB Receptacle

### In The Box

- Wireless Mouse
- USB 2.4G Receiver
- Type C Cable
- Docs

All buttons are fully programmable via the dedicated Web Control Centre.

### Web Control Centre and Help Guide

Scan the QR and Watch Quick Tutorial Videos.  
<https://www.amkette.com/sw/xsflowplus>

---

### DPI Settings

All buttons on the XS Flow Plus are fully programmable using the Web Control Centre. Access it at <https://www.amkette.com/sw/xsflowplus>

#### Web Control Centre And Special Features

- Easy Device Switch:** The Device Switch function is predefined to Button 2 and can also be assigned to any other button using the Web Control Centre, allowing quick switching between connected devices.
- RGB Modes:** The mouse features 7 RGB lighting modes plus an Off mode. Press the Scroll button + Forward button together to cycle through the RGB modes.
- Hall Effect Magnetic Horizontal Scroll:** The high-precision Hall effect Magnetic Horizontal scroll supports smooth horizontal scrolling and is fully programmable through the Web Control Centre.
- Show Desktop & OS Switching**

#### Device Switching & Other Functions

• **Easy Device Switch:** The Device Switch function is predefined to Button 2 and can also be assigned to any other button using the Web Control Centre, allowing quick switching between connected devices.

• **RGB Modes:** The mouse features 7 RGB lighting modes plus an Off mode. Press the Scroll button + Forward button together to cycle through the RGB modes.

• **Hall Effect Magnetic Horizontal Scroll:** The high-precision Hall effect Magnetic Horizontal scroll supports smooth horizontal scrolling and is fully programmable through the Web Control Centre.

#### Show Desktop & OS Switching

- **OS Switching:** Long-pressing the same button switches the mouse from Windows to macOS, enabling seamless use across different operating systems without changing settings manually.
- **Show Desktop:** The Show Desktop function is predefined to Button 5 and can be reassigned to any button using the Web Control Centre.

#### Seamless Power Controls

- **Power Saving Modes:** The mouse enters standby mode after 1 minute of inactivity and deep sleep mode after 15 minutes of inactivity.
- **Customizable Sleep Timing:** The power-saving time duration is fully programmable through the web control centre, allowing the standby and sleep timings to be adjusted according to the user preference.

#### Polling Rates

- **Default Polling Rate:** For 2.4GHz and wired, the default polling rate is 1000Hz for maximum performance, while Bluetooth mode defaults to 250Hz.
- **Programmable Polling Rate:** In wired and 2.4G modes, the polling rate is available in four levels—125Hz, 250Hz, 500Hz, and 1000Hz—and is programmable via the Web Control Centre according to the user preference.

#### Web Control Centre and Help Guide

Scan the QR and Watch Quick Tutorial Videos.  
<https://www.amkette.com/sw/xsflowplus>

### Connecting via USB 2.4GHz

2.4G mode is indicated by a solid green light.

If you need to re-pair the dongle with the mouse, long-press the easy Device Switch button until the 2.4G Green indicator blinks, then plug in the receiver to complete pairing.

### Connecting via Cable

When the mouse is connected via cable, it will automatically switch to wired mode, and all other wireless modes will be disabled.

The wired mode is indicated by a red light situated below the DPI button.

### Web Control Centre And Special Features

All buttons on the XS Flow Plus are fully programmable using the Web Control Centre. Access it at <https://www.amkette.com/sw/xsflowplus>

#### Device Switching & Other Functions

• **Easy Device Switch:** The Device Switch function is predefined to Button 2 and can also be assigned to any other button using the Web Control Centre, allowing quick switching between connected devices.

• **RGB Modes:** The mouse features 7 RGB lighting modes plus an Off mode. Press the Scroll button + Forward button together to cycle through the RGB modes.

• **Hall Effect Magnetic Horizontal Scroll:** The high-precision Hall effect Magnetic Horizontal scroll supports smooth horizontal scrolling and is fully programmable through the Web Control Centre.

#### Show Desktop & OS Switching

- **OS Switching:** Long-pressing the same button switches the mouse from Windows to macOS, enabling seamless use across different operating systems without changing settings manually.
- **Show Desktop:** The Show Desktop function is predefined to Button 5 and can be reassigned to any button using the Web Control Centre.

#### Seamless Power Controls

- **Power Saving Modes:** The mouse enters standby mode after 1 minute of inactivity and deep sleep mode after 15 minutes of inactivity.
- **Customizable Sleep Timing:** The power-saving time duration is fully programmable through the web control centre, allowing the standby and sleep timings to be adjusted according to the user preference.

#### Polling Rates

- **Default Polling Rate:** For 2.4GHz and wired, the default polling rate is 1000Hz for maximum performance, while Bluetooth mode defaults to 250Hz.
- **Programmable Polling Rate:** In wired and 2.4G modes, the polling rate is available in four levels—125Hz, 250Hz, 500Hz, and 1000Hz—and is programmable via the Web Control Centre according to the user preference.

#### Web Control Centre and Help Guide

Scan the QR and Watch Quick Tutorial Videos.  
<https://www.amkette.com/sw/xsflowplus>

### Connection Guide

NOTE: Before proceeding with the connection process, please ensure that the mouse is charged using the provided Type-C cable.

#### Connecting via Bluetooth

You can connect up to 3 Bluetooth Devices simultaneously and seamlessly switch between them using the Device Switch Button.

**PAIRING**  
Blinks Fast

**CONNECTING**  
Search and Connect on your device

**SWITCHING**  
Single Press

On switching modes, the Blue indicator will blink slowly while trying to reconnect to the last paired device.

- If no device is found, the Blue indicator will blink rapidly to indicate pairing mode.
- After successful pairing, the Blue indicator will stay solid for 3 seconds and then turn off.
- To switch between BT1, BT2, and BT3, press the Device Switch button once.
- To force pair the mouse, long-press the Device Switch button until the Bluetooth indicator starts blinking rapidly.

#### Connecting via Cable

2.4G mode is indicated by a solid green light.

If you need to re-pair the dongle with the mouse, long-press the easy Device Switch button until the 2.4G Green indicator blinks, then plug in the receiver to complete pairing.

#### Connecting via Cable

When the mouse is connected via cable, it will automatically switch to wired mode, and all other wireless modes will be disabled.

The wired mode is indicated by a red light situated below the DPI button.