

DOCUMENT DETAILS V1	
Product:	XS Flow 2 Speed
Type:	QSG
Date Updated:	03-04-2026
GSM:	250

XS FLOW 2 SPEED

Compatible OS

Customer Care

Amkette House, C-6/d, Okha Phase - II, New Dohi - 110020
 8000-11-9090 (Toll Free)
 9:30 AM - 6:00 PM
 Mon - Sat
 Scan For Whatsapp
 techsupport@amkette.in
 www.amkette.com/register

For Hassle Free Service Register Your Product

Specifications

Interface	: Wired + 2.4GHz Wireless + Bluetooth x 3
Buttons	: 8 Buttons
Mouse DPI	: 400-800-1600-2400-3200-6400-8000
Polling Rate	: BT: 250Hz - 2.4G: 1000Hz - Wired: 1000Hz
Sensor	: PAW 3220
Chipset	: BK3433
Scroll Wheels	: Metallic Adaptive Hyper-Fast Main Scroll + Metallic Slide Scroll
Material	: ABS plastic + metal scroll components
Battery	: 800mAh
Switch Type	: PTFE Teflon feet
Feet	: T10g
Product Dimensions	: 117.4 x 75 x 42.5 mm

Warranty

Amkette XS Series Flow 2 Speed Dual Scroll Rechargeable Mouse is backed by 2 year performance warranty against any manufacturing defects in material or workmanship from the date of original purchase. This warranty entitles the purchaser to get the product repaired or replaced at its discretion under the following conditions:
 The warranty applies to the original purchaser; Proof of original purchase is required.
 The warranty does not cover the damage caused by misuse, abuse or improper storage.
 In no event shall Amkette be responsible for any direct, incidental, consequential or other damages of any kind.
 Please contact our technical support line and/or send the defective product, postage pre-paid, together with the proof of purchase to our Customer Care Service Center to avail warranty service. Return charges will be paid by us.

XS SERIES
by AMKETTE

FLOW 2 SPEED

Dual Scroll Rechargeable Bluetooth Mouse

QUICK START GUIDE

Web Control Centre: <https://www.amkette.com/sw/xsflow2speed>

Know Your Mouse

1 Vertical Scroll Wheel	2 Show Desktop	3 DPI Button
4 Horizontal Scroll Wheel	5 Forward Button	6 Backward Button
7 Type C Input	8 Mode Switch / Off Button	9 Left MB Indicator
10 Device Switch	11 USB SRN	12 USB Receptacle

The metallic hyper fast adaptive scroll wheel gives controlled tactile scrolling in normal use and rapid free spin scrolling for long pages.

All buttons are fully programmable via dedicated Web Control Centre.

Wireless Mouse

USB 2.4G Receiver

Type C Cable

Docs

Web Control Centre and Help Guide

Scan the QR and Watch Quick Tutorial Videos.
<https://www.amkette.com/sw/xsflow2speed>

Web Control Centre And Special Features

All buttons on the XS Flow 2 Speed are fully programmable using the Web Control Centre. Access it at <https://www.amkette.com/sw/xsflow2speed>

Device Switching & Other Functions

- **Programmable BT Device Switch:** The Device Switch function is located on the back button by default and can be reassigned to any other button using the Web Control Centre for easier access.
- **Hyper-Fast Adaptive Scroll:** The metallic adaptive hyper-fast main scroll delivers controlled tactile scrolling for everyday use and rapid free-spin scrolling for long documents and timelines.
- **Hall Effect Magnetic Horizontal Scroll:** The high-precision Hall effect programmable through the Web Control Centre.
- **Show Desktop & OS Switching:** The Show Desktop function is preferred to Button 2 and can be reassigned to any button using the Web Control Centre.
- **OS Switching:** Long-pressing the same button switches the mouse from Windows to macOS, enabling seamless use across different operating systems without changing settings manually.

DPI Settings

- **Pre-programmed DPI Levels:** The mouse comes with 7 pre-programmed DPI levels of 400, 800, 1600, 2400, 3200, 6400 and 8000, which can be switched using the DPI button.
- **Custom DPI Adjustment:** The number of DPI levels and their values (200 to 8000) can be customized through the Web Control Centre, allowing upto 7 DPI levels to be set as preferred.
- **Seamless Power Controls**
 - **Power Saving Modes:** The mouse enters standby mode after 1 minute of inactivity and deep sleep mode after 15 minutes of inactivity.
 - **Customizable Sleep Timing:** The power-saving time duration is fully programmable through the web control centre, allowing the standby and sleep times to be adjusted according to the user preference.
- **Polling Rates**
 - **Default Polling Rate:** For 2.4GHz and wired, the default polling rate is 1000Hz for maximum performance. While Bluetooth mode defaults to 250Hz.
 - **Programmable Polling Rate:** In wired and 2.4G modes, the polling rate is available in four levels—125Hz, 250Hz, 500Hz, and 1000Hz—and is programmable via the Web Control Centre according to the user preference.

Show Desktop & OS Switching

Web Control Centre and Help Guide

Connecting via Bluetooth

You can connect up to 3 Bluetooth Devices simultaneously and seamlessly switch between them using the Device Switch Button.

NOTE: Before proceeding with the connection process, please ensure that the mouse is charged using the provided Type-C cable.

Connecting via USB 2.4GHz

To pair with a new receiver, long-press the Device Switch button for 3 seconds.

Connecting via Cable

When the mouse is connected via cable, it will automatically switch to wired mode, and all other wireless modes will be disabled.

When the mouse is connected in wired mode, a red indicator light will appear below the horizontal scroll.

Connection Guide

Pairing

FRONT

BACK