

DOCUMENT DETAILS V1	
Product:	XS Natural Plus
Type:	QSG
Date Updated:	22-12-2025
Paper Type	220 GSM Thick Card

XS Natural Plus QSG

Font

Specifications

Interface	: Wired + 2.4GHz Wireless + Bluetooth x 3
Buttons	: 7 Buttons
Mouse DPI	: 400 / 800 / 1200 / 1600 / 2400 / 3200 / 6400
Scrolling Rate	: BT: 250Hz - 2.4G: 1000Hz - Wired: 1000Hz
Sensor	: Instant S203
Chipset	: BK3633
Scroll Wheels	: Metallic main scroll + Horizontal scroll
Material	: ABS plastic + metal scroll components
Battery	: 800mAh
Switch Type	: Hano silent switches, 10 million clicks
Feet	: PTFE Teflon feet
Product Weight	: 95g
Product Dimensions	: 106 x 73 x 68mm

Warranty

Amkette XS Series Natural Plus Dual Scroll Rechargeable Bluetooth Mouse is backed by 2 year performance warranty against any manufacturing defects in material or workmanship from the date of original purchase. This warranty entitles the purchaser to get the product repaired or replaced at its discretion under the following conditions:

The warranty does not cover the damage caused by misuse, abuse or improper storage.

In no event shall Amkette be responsible for any direct, incidental, consequential or other damages of any kind.

Please contact our Technical Support Line and/or send the defective product, postage pre-paid, together with the proof of purchase to our Customer Care Service Center to avail warranty service. Return charges will be paid by us.

Customer Care

Amkette House, C-64/4, Okhla Phase - II, New Delhi - 110020
 +91 9312691448 (9:30 AM - 6:00 PM)
 1800-11-9990 (Toll Free)
 techsupport@amkette.in
 www.amkette.com/register

Back

Web Control Centre and Help Guide

Scan the QR and Watch Quick Tutorial Videos. Access the Web Control Centre at <https://www.amkette.com/sw/xsnaturalplus>

Compatible OS

Seamless Power Controls

- Power Saving Modes: The mouse enters standby mode after 1 minute of inactivity and deep sleep mode after 15 minutes of inactivity.
- Customizable Sleep Timing: The power-saving time duration is fully programmable through the web control centre, allowing the standby and sleep timings to be adjusted according to the user preference.
- Default Polling Rate: For 2.4GHz and wired, the default polling rate is 1000Hz for maximum performance, while Bluetooth mode defaults to 250Hz.
- Programmable Polling Rate: In wired and 2.4G modes, the polling rate is available in four levels—125Hz, 250Hz, 500Hz, and 1000Hz—and is programmable via the Web Control Centre according to the user preference.
- Lower the polling rate better the battery life of the mouse.

XS SERIES

Smart • Simple • Superior

XS Series by Amkette is a line of high-performance IT peripherals crafted to deliver a superior experience through smart functionality, minimalist design, and uncompromising quality. Built for professionals and creators, XS Series products embody what we stand for: Smart. Simple. Superior.

Web Control Centre And Special Features

All buttons on the XS Natural Plus are fully programmable using the Web Control Centre. Access it at <https://www.amkette.com/sw/xsnaturalplus>

- Programmable Device Switch: The Device Switch function is located on the back button by default and can be reassigned to any other button using the Web Control Centre for easier access.
- OLED Display: The built-in OLED display shows key information at a glance, including the active connection mode, current DPI level, and battery levels.
- Pre-programmed DPI Levels: The mouse comes with 7 pre-programmed DPI levels of 400, 800, 1200, 1600, 2400, 3200, and 6400, which can be switched using the DPI button.
- Custom DPI Adjustment: The number of DPI levels and their values (200 to 6400) can be customized through the Web Control Centre, allowing upto 7 DPI levels to be set as preferred.

Connecting via USB 2.4GHz

To pair with a new receiver, switch to 2.4G mode and long-press the mode switch button until the indicator on the display starts blinking. Once paired, the connection will be established automatically.

Connecting via Cable

When the mouse is connected using a cable, it automatically switches to wired mode, and all wireless modes are disabled.

NATURAL PLUS

Dual Scroll Rechargeable Bluetooth Mouse

QUICK START GUIDE

Web Control Centre: <https://www.amkette.com/sw/xsnaturalplus>

Know Your Mouse

- 1 Scroll Wheel
- 2 DPI Button
- 3 Forward Button
- 4 OLED Display
- 5 Horizontal Wheel
- 6 ON/OFF Switch
- 7 Backward Button
- 8 Type C Input

PAIRING

Mode Switch Press

SEARCH AND CONNECT

XS Natural Plus

Search and Connect on your device

SWITCHING

Mode Switch Press

SEARCH AND CONNECT

XS Natural Plus

Search and Connect on your device

All buttons are fully programmable via the dedicated Web Control Centre.

Connecting via Bluetooth

You can connect up to 3 Bluetooth devices simultaneously and seamlessly switch between them using the Device Switch Button.

PAIRING

Mode Switch Press

SEARCH AND CONNECT

XS Natural Plus

Search and Connect on your device

SWITCHING

Mode Switch Press

SEARCH AND CONNECT

XS Natural Plus

Search and Connect on your device

Connection Guide

NOTE: Before proceeding with the connection process, please ensure that the mouse is charged using the provided Type-C cable.

OLED Display Overview

DPI Level: 400 / 800 / 1600 / 2400 / 3200 / 6400

Battery Level: 1600mAh

In The Box

- Wireless Mouse
- USB 2.4G Receiver
- Type C Cable
- Docs

Connecting via Bluetooth

You can connect up to 3 Bluetooth devices simultaneously and seamlessly switch between them using the Device Switch Button.

PAIRING

Mode Switch Press

SEARCH AND CONNECT

XS Natural Plus

Search and Connect on your device

SWITCHING

Mode Switch Press

SEARCH AND CONNECT

XS Natural Plus

Search and Connect on your device

Z Fold