

DOCUMENT DETAILS V1.1	
Product:	Katana X2 TKL Wireless
Type:	User Manual
Date Updated:	13-05-2025

FRONT

BACK

WARRANTY STATEMENT

Amkette EvoFox Katana X2 TKL Tri-Mode Wireless Mechanical Keyboard is backed by a 1 year performance warranty against any manufacturing defects in material or workmanship from the date of original purchase. This warranty entitles the purchaser to get the product repair or replaced under the following conditions:

The warranty applies to the original purchaser. Proof of original purchase is required.

The warranty does not cover the damage caused by misuse, abuse or improper storage.

In no event shall Amkette be responsible for any direct, incidental, consequential or other damages of any kind.

Please contact our Technical Support Line and/or send the defective product, postage pre-paid, together with the proof of purchase to our Customer Care Service Center to avail warranty service. Return postage will be paid by us.

CUSTOMER CARE CENTER

Amkette House, C-64/4, Okhla Phase – II, New Delhi – 110020

1800-11-9090 (Toll Free)
(9:30 AM - 6:00 PM)

+91 9312491448
(9:30 AM - 6:00 PM)

techsupport@amkette.in

For Hassle Free Service Register Your Product
www.amkette.com/register

Katana X2

TKL TRI-MODE WIRELESS MECHANICAL KEYBOARD

QUICK START GUIDE

PLAY WITH POWER

The Nine-Tailed Fox is ready to unleash a gaming force never seen before. Channelise your inner Gaming Ninja with gaming peripherals and devices crafted for gamers who choose to stay every time they play. Console or mobile, casual or pro, this tribe is ready to welcome you!

SPECIFICATIONS

Professional Grade **HUANO RED SWITCHES**

Key Life	50 Million
Actuation Distance	2.0±0.4 mm
Actuation Force	60±10 gf
Bottom Out Distance	4.0±0.4 mm

KEYBOARD SPECIFICATIONS :

Keyboard Type	Mechanical	Switch Socket	3 Pin User Replaceable
Interface	Wired + 2.4 GHz + Bluetooth	Multimedia Control	Yes w/ Volume Controller
Switch Type	Huano Silent Red Switches	Cable	Detachable 1.8m Type-C
No. of Keys	83 Keys	Polling Rate	1000Hz
Backlighting	Rainbow with 18 Effects	Battery	4000mAh
Anti-Ghosting	n-Key Rollover	Product Dimensions & Weight	336 x 142 x 43 (mm), 766g

SYSTEM REQUIREMENTS

Windows 10/11

macOS

Linux

android

iOS

ALL KEYS ANTI GHOSTING

With full n-key rollover and all-keys anti-ghosting, every keypress is accurately registered—even when multiple keys are pressed simultaneously.

OS MODE SWITCH

Windows

All Multimedia functions works with **[Fn]** key. There's a Dedicated Co-Pilot button on F5 key. All the Windows shortcut keys works in Windows Mode.

Mac OS

All Multimedia functions works with pressing **[Fn]** key. All the Mac Modifier Keys works in Mac Mode.

KNOW YOUR KEYBOARD

WHAT'S IN THE BOX

Katana X2 TKL Wireless Mechanical Keyboard

USB Type C Cable

Key Puller

4 x Huano Red Switches

USB 2.4G Receiver

Docs

CHARGE YOUR DEVICE

Before proceeding with the connection process, please ensure your Keyboard is charged using the provided Type-C cable.

In Bluetooth mode you can see the Battery percentage of your Keyboard on the connected device.

SWITCHING MODES & DEVICES

SELECTING MODES

- 2.4GHz Mode
- Wired Mode
- BT Mode

SWITCHING DEVICES

BT Device 1:

+

BT Device 2:

+

BT Device 3:

+

HOW TO SWAP KEYS & SWITCHES

STEP-1

Use the Keycap Puller to gently remove the desired Keycap.

STEP-2

Remove the existing Switch using the Switch Puller. Ensure to orient the Switch Puller so as to engage the clips on the Switch.

STEP-3

Place the Replacement Switch in the same orientation as the removed Switch, ensuring that the Legs are not being bent. Press down firmly.

STEP-4

Place the removed Keycap back on to the replaced Switch and press down firmly.

Scan this QR code to access the video manual on switch replacement.

MULTIFUNCTION VOLUME CONTROLLER

FOR VOLUME CONTROLS: Default Mode

Clockwise	Increase Volume
Anti-Clockwise	Decrease Volume
Single Press	Mute

FOR BRIGHTNESS LEVEL CONTROLS: Long Press to Activate

Clockwise	Increase Brightness
Anti-Clockwise	Decrease Brightness
Single Press	Change Modes

KEYBOARD LED INDICATION

	CAPS LOCK
	WINDOWS LOCK
	2.4GHz WIRELESS MODE
	BLUETOOTH MODE

CONNECTING VIA USB 2.4 GHZ

Toggle the Mode Switch button to 2.4G mode, then take out the 2.4G receiver and plug it into your device.

TOGGLE TO

2.4GHz Mode

PAIRING

Long Press

Pairing Process: Insert the the 2.4G receiver in to your PC after long pressing the Fn + 4 buttons.

CONNECTING VIA BLUETOOTH

You can connect upto 3 Bluetooth Devices simultaneously and seamlessly switch between them.

TOGGLE TO

BT MODE

PAIRING

LONG PRESS

BLINK FAST

CONNECTING

Search and Connect on your device

Repeat the above process for Switching to Bluetooth Device 2 and 3 by pressing **[Fn] + 2** or **[Fn] + 3** respectively.

CONNECTING VIA WIRED MODE

Connect the Type-C cable to the keyboard, then plug the other end into your device.

TOGGLE TO

Wired Mode

Note: You can use your own Type C cable if needed.

BACKLIGHTING CONTROLS

Change Effects

Turn OFF Backlighting

Backlighting Direction Change

Increase LED Effect Speed

Decrease LED Effect Speed

Increase LED Brightness

Decrease LED Brightness

MULTIMEDIA SHORTCUT KEYS

Access media controls efficiently with **[Fn]** key and any key below respectively.

F1

Music

F2

Mute

F3

Volume -

F4

Volume +

F5

Copilot/Siri

F6

Stop

F7

Previous Song

F8

Play & Pause

F9

Next Song

F10

Screenshot

F11

Show Desktop

F12

Lock Screen

KATANA X2 TKL WIRELESS QSG